

HAMILTON AIR®

3143 Production Drive • Fairfield, Ohio 45014 • 513-874-3733

Typical Kroger Pharmacy Wiring Detail

Remote Location with Turbine Blower Back Located in Canopy Attic

Reference Drawings:

99-1032	Kroger Secure Cabinet
99-1037	Kroger Reverse HA1000 OH System
99-1038	Kroger Reverse PIR System
99-1040	Standard HA1000 OH with 400DD
99-1049	Kroger PIR System

Conduit	Junction	Description	Wire
C1	J2 - J5	Audio, system interconnect, video	CAT5 (2), Coax (2)
C2	J2 - J3	System interconnect, PIR	CAT5, 3 Cond.
C3	J4 - J5	Video	Coax (2)
C4	J1 - J4	VeriFone interconnect and power	CAT5, VeriFone Ext. Cable, 2 Cond.
C5	J5 - J6	Remote Turbine Blower Pack	12/3

Junction	Conduit	Description
J1	C4	4"x4" junction box located under counter for VeriFone credit card machine connections
J2	C1 & C2	4"x4" junction box located under counter for Audio / Video Connections
J3	C2	4"x4" junction box located above ceiling for interior tube station interconnect
J4	C4 & P2	Secure Cabinet, Credit card and video
J5	C1 & P1	HA1000 Customer Unit
J6	C5	HA1000 Customer Unit to Remote Turbine Blower Pack in Canopy Attic

Wire	Conduit	Description	Locations
CAT5	C1	Audio	HA1000 handset to Kroger PBX unit
CAT5	C1 & C2	System interconnect	HA1000 to Interior tube station above ceiling
Coax (2)	C1 & C3	Video, 2-way	Secure Cabinet video to 5550 interior video station
3 Cond.	C2	PIR Vehicle detection	Chime and power supply located under counter to PIR located in canopy
CAT5	C4	VeriFone MX760 (Future)	Secure Cabinet to junction box under counter
2 Cond.	C4	VeriFone MX760 (Future)	Secure Cabinet to junction box under counter
VeriFone Ext.	C4	VeriFone QX720	Secure Cabinet to junction box under counter
12/3	C5	Remote Turbine Blower Pack	HA1000 Customer Unit to Remote Turbine Blower Pack in Canopy Attic