



Introducing  
the

**COMBO****GARD**PRO

# COMBOGARDPRO

- **FEATURES**

- 10 Codes (Manager and 9 User)
- Time Delay (99 min delay, 19 open)
- Code length (6 to 9)
- PC programmable Software
- Fully Key Pad configurable
- Audit (63 first in first out, non-erasable)

# COMBOGARDPRO

Lock Setup  
Via  
The  
Key Pad  
Tutorial

# COMBOGARDPRO

## Lock Setup Steps

- Exit Pre-set mode
- Select Code Length
- Install Users
- Select Additional Features
- Finalizing Configuration

# COMBOGARDPRO

- Exit Pre-set mode

Step 1) Press and Hold '0' key until unit signals twice.

Step 2) Enter the default Manger Code  
5-5-5-5-5-5.

- Lock will open and is now in the Setup and Test mode.

# COMBOGARDPRO

- **Select Code Length**

- Example: How to change code length from 6 to 9 digits
- Enter: 5-5-5-5-5-5 Hold down the last digit until the lock signals twice and the LED stays on.
- PRESS '8' key.
- PRESS '9' (the desired code length), then PRESS '0'
- Re-enter: PRESS '9', then PRESS '0', to confirm.
- The code length has now been change to 9 digits.
- To verify: Enter: 5-5-5-5-5-5-5-5-5, the lock will open.

# COMBOGARDPRO

- **Select Code Length**

- Example: How to change code length from 9 to 6 digits
- Enter: 5-5-5-5-5-5-5-5-5 Hold down the last digit until the lock signals twice and the LED stays on.
- PRESS '8' key.
- PRESS '6' (the desired code length), then PRESS '0'
- Re-enter: PRESS '6', then PRESS '0', to confirm.
- The code length has now been change to 9 digits.
- To verify: Enter: 5-5-5-5-5-5, the lock will open.

The lock is now set to operate using 6 digits codes.

# COMBOGARDPRO

- **Install Users (1,2, & 9)**
- Enter: 5-5-5-5-5-5 Hold down the last digit until the lock signals twice and the LED stays on.
- PRESS '1' key.
- Select User ID: '1'
- Enter user code: 1-1-1-1-1-1; re-enter code 1-1-1-1-1-1
- User is installed.
- Enter: 1-1-1-1-1-1 to verify. Lock will open.



# COMBOGARDPRO

- **Install Users (1,2, & 9)**
- Enter: 5-5-5-5-5-5 Hold down the last digit until the lock signals twice and the LED stays on.
- PRESS '1' key.
- Select User ID: '2'
- Enter user code: 2-2-2-2-2-2; re-enter code 2-2-2-2-2-2
- User is installed.
- Enter: 2-2-2-2-2-2 to verify. Lock will open.

# COMBOGARDPRO

- **Install Users (1,2, & 9)**
- Enter: 5-5-5-5-5-5 Hold down the last digit until the lock signals twice and the LED stays on.
- PRESS '1' key.
- Select User ID: '9'  
(User 9 will later be enabled to override time delay)
- Enter user code: 9-9-9-9-9-9; re-enter code 9-9-9-9-9-9
- User is installed.
- Enter: 9-9-9-9-9-9 to verify. Lock will open.

# COMBOGARDPRO

## Lock Programmable Feature Chart.

MODE	TIME DELAY OVERRIDE	DUAL CODE	SILENT ALARM
0			
1	√		
2		√	
3	√	√	
4			√
5	√		√
6		√	√
7	√	√	√

# COMBOGARDPRO

## Added Lock Features

- Enter: 5-5-5-5-5-5 Hold down the last digit until the lock signals twice and the LED stays on.
- PRESS '8' key.
- Enter '0' (this will maintain the current code length)
- Enter Option '5' (Time Delay Override and Silent Alarm)
- Re-enter '0' then '5' to confirm

# COMBOGARDPRO

- **Finalizing and Exiting Setup**

Once the Manager changes his or her code, the configuration is frozen.

Special Function #8 is no longer available.

Un-enrolled Users are blocked and can not be added later.

Also, the lock's operational mode can no longer be changed.

## To change Manger code:

- Enter: 5-5-5-5-5-5 Hold down the last digit until the lock signals twice and the LED stays on.
- PRESS '0' key.
- Enter New Manager code
- Example: '1-2-3-4-5-6'
- Re-enter '1-2-3-4-5-6' to confirm.

# COMBOGARDPRO

## **The lock is now configured as follows:**

- Users 1, 2, and 9 are active.
- Users 3, 4, 5, 6, 7, and 8 are blocked and can not be enrolled later.
- Time delay Override is Enabled. (User 9)
- Silent Alarm is Enabled.

# COMBOGARDPRO

## How to Changing Time Values

We will set the following time values:

Delay 1 minute

Open 1 minute

- **Time Delay Setup**

- Enter Master code '1-2-3-4-5-6' Hold down the last digit until the lock signals twice and the LED stays on.
- PRESS '9' key.
- Enter the desired delay period: '0-1'
- Enter open period '0-1'
- Re-enter '0 -1- 0 -1' to confirm

# COMBOGARDPRO

## **The lock is now configured as follows:**

- Users 1, 2, and 9 are active.
- Users 3, 4, 5, 6, 7, and 8 are blocked and can not be enrolled later.
- Time delay Override is Enabled. (User 9)
- Silent Alarm is Enabled.
- One minute Time Delay with a one minute Open Period.



# COMBOGARDPRO

To start the delay period, enter either the Manager or a User code.

To override the delay Enter User # 9's code.

Note: If Time Delay is active it can only be deactivated or delay value decreased in the Open Period. Selecting '0000' deactivates the Time Delay Feature.

# COMBOGARDPRO

This concludes the lock setup  
with via the key pad.

Thank You